

Model 510-225 Load Switch



Model 810-225 Flasher



The commitment to quality and reliability found in EDI Signal Monitors continues with the Model 510-225 solid state Load Switch and Model 810-225 Flasher.

The heavy duty extruded aluminum heat sink chassis of the Model 510 / 810 is designed to allow the triac device to operate with the full load current at high temperature (+74°C) without exceeding the manufacturer "Maximum Allowable Case Temperature" triac device specification. This helps ensure long life and reliable operation from the triac device. It can be shown that device reliability is logarithmically related to device operating temperature.

Model 510-225 Operational Features

- ✓ Meets NEMA TS1-1994 & NEMA TS2-2003 requirements.
- ✓ 10 Amp RMS Maximum Load Current over full NEMA temperature range of -34°C to +74°C
- ✓ Operating Voltage Range: 120 to 270 VAC
- ✓ Zero crossing: Less than 5 degrees of zero voltage point
- ✓ Isolation greater than 2000 volts
- ✓ Off state leakage less than 10 mA peak
- ✓ Maximum input current less than 20 mA
- ✓ Peak Inverse Voltage: 600V
- ✓ One cycle surge: 250 Amps peak.
- ✓ Noise rejection is greater than ±300V peak
- ✓ Three electrically independent circuits
- ✓ Dimensions: L = 8.025" x H = 4.170" x W = 1.475"

Model 810-225 Operational Features

- ✓ Meets NEMA TS1-1994 & NEMA TS2-2003 requirements.
- ✓ 15 Amp RMS per circuit Maximum Load Current over full NEMA temperature range of -34°C to +74°C
- ✓ Operating Voltage Range: 120 to 270 VAC
- ✓ Zero crossing: Less than 5 degrees of zero voltage point
- ✓ Isolation greater than 2000 volts
- ✓ 56 Flashes/Minute, Internal Oscillator Controlled
- ✓ Flash Rate stable when used with generators or inverters
- ✓ Peak Inverse Voltage: 600V
- ✓ One cycle surge: 250 A peak.
- ✓ Noise rejection is greater than ±300V peak
- ✓ Dual Output Circuits
- ✓ Dimensions: L = 8.025" x H = 4.170" x W = 1.475"

EBERLE DESIGN INC.

3510 East Atlanta Avenue
Phoenix, AZ 85040 USA
www.EDITraffic.com

Tel (480) 968-6407
Fax (602) 437-1996

